

Z-URC™

(Z-Wave Enable Universal Remote)

For controlling your AV equipment and home automated devices.

Z-URC™ 550EU



Extra set top box dedicated keys for full set top box control



2 x 8 Groups/Scene up to 232 Z-Wave devices



Hassle free XpressZetup™ for Z-Wave setup in 3 easy steps

Hardware Key Spec and Features

Supported Devices	All AV appliances plus Z-Wave enabled devices
Max IR devices	8 devices with learning
Infra Red signal Transmission distance	Normal mode (1x IR diode) 8 meter in straight line, 5 meters within 30 degree conical Boost mode (3 x IR diode) 10 meter in straight line, 8 meters within 30 degree vertical angle, 5 meter within 120 degree horizontal
RF control	Z-Wave compliant switch, dimmer devices, door sensor, curtain and thermostat. etc...
Max Z-Wave devices	Max. 232 devices in 16 groups
Z-Wave covering range	Point to point approx. 30 meter (unlimited range through mesh networking)
Power source	3 X AAA Battery

Software Key Spec and Features

Controlled IR devices	TVs, Optical disc players, Cable/Sat boxes, Audio equipment covers worldwide brands
Command learning	IR control commands, max 455KHz
User Interface	User friendly XpressZetup™, powerful Advance Setup
Users programmable	Group Controls, Association Controls, Scene modes and Gateway Integration

Ordering part number: BW8332

Remotec

Rm 2907-2908, Skyline Tower, 39 Wang Kwong Road, Kowloon Bay, Hong Kong.
Tel: (852) 2314 0330 Fax: (852) 2314 1006 E-mail: rtlsales@remotec.com.hk

Website: <http://www.remotec.com.hk>